

CONTROL^D CONTROL DEVICE

for proportional solenoid valve control

FEATURES

- Control device for PWM (pulse-width modulated) proportional solenoid valve control
- Designed for open-loop, closed-loop and double-loop (cascaded) control
- Suitable for the control of flow, pressure, temperature, force etc.
- · Integrated display and LEDs
- Control parameters adjustable via software (DigiCom, USB interface)
- Auto-Adapt function/button for automatic adjustment of the Control device to the control valve

A special feature of the $\mathsf{Control}^D$ is the "ASCO-Digi Com " software supplied for optimum adjustment over PC. Setpoint and feedback values can be viewed at the same time. Other functions are valve diagnostics, parameter setting and maintenance.



Ambient temperature -20°C to +50°C

CONSTRUCTION

Body PA (polyamide)

Degree of protection IP20

Electrical connection Pluggable terminal block (0,08 - 1,5 mm²)

Mounting DIN-EN 50022 rail

ELECTRICAL CHARACTERISTICS

Supply voltage (U_N) 24 V DC ±10 %, max. ripple 10 %

or 12 V DC +15 % -5 %, max. ripple 10 %

Max. current of

proportional solenoid valve 2 A

Setpoint input 0 - 10 V DC, 0 - 20 mA, 4 - 20 mA **Sensor input** 0 - 10 V DC, 0 - 20 mA, 4 - 20 mA


Feedback output 0 - 10 V, 0 / 4 - 20 mA

Ramp ON/OFF

adjustable between 0,1 and 20 seconds

Adjustable switching frequency 20 to 2000 Hz

CONTROLO



SPECIFICATIONS

	description	catalogue number
	Control device - 12 V DC	60300117
6	CONTROL ^D control device - 24 V DC	60300118

PROPORTIONAL VALVES SUITABLE FOR CONTROL APPLICATIONS


description	series	illustration	catalogue page
3-port proportional valve for pressure control	602		see " <u>Proportional Technology</u> " on: www.asco.com
Posiflow proportional solenoid valves	202-203		See " <u>Proportional Technology</u> " on: www.asco.com

All rights reserved




DIMENSIONS (mm), **WEIGHT** (kg) weight: 0,153 kg





CONNECTOR PINNING



pin	description	pin	description
1	V DC IN/ + supply	11	Setpoint
2	GND IN/ ground	12	GND setpoint
3	Protective earth PE	13	Digital input
4	Frequency input	14	GND Digital input
5	Sensor supply voltage +	15	Valve / coil connection
6	Analog input 1	16	GND valve
7	GND sensor supply voltage	17	Digital output
8	Sensor supply voltage +	18	GND Digital output
9	Analog input 2	19	GND Analog output
10	GND sensor supply voltage	20	Analog output

ACCESSORIES

description	catalogue number
"ASCO-DigiCom" Control ^D software on CD-ROM (supplied with the controller)	88100893
USB cable for Control ^D to PC connection (to be ordered separately)	88100894